Irrimec Dosidis+ IP

Part 1: Setup on the Dosidis+ Device

What do you need?

- Device switched on and ready
- Appropriate SIM card (Raindancer or your own)
- Access data (APN) – you will receive this from your dealer or service provider

Setup steps:

First, insert the SIM card into the device. Detailed instructions can be found in the manual under section 7.C (page 32).

1. Press the **OK** button on the Dosidis+ device to enter the menu.
2. Navigate to the menu **"Data connection 7.0"**.
3. Under submenu **7.1**, activate **MODEM GSM**.
4. Under submenu **7.3**, you will find the IMEI number. Write this down, as you will need it later for integration into Raindancer.
5. Submenu **7.5** allows you to enter the APN settings. These depend on the SIM card used:
   - 2024 and before Connekt: **connectivity.io**
   - 2025 EU2: **global.melita.io**
6. Next, go to submenu **7.6 "SERVER CONNECTION"** and enter the following details:
   - **URL:** „167.233.13.200“
   - **TCP/IP Port:** „44447“
7. sub menu **7.8 server connection = enable**
8. Finally, verify in the menu **"SERVER CONNECTION"** that the internet connection is shown as **"active"**.

What to do if the connection fails:

- Verify the APN, URL, and port data have been correctly entered.
- Check network reception at your location.
- Restart the device to establish a fresh connection.

> We recommend for Using the remote control a **firmware** of
>
> - Dosidis+ of Irreg13 3 03 (11.02.2026) or higher
>
> - Dosidis2 of Irreg12 6.02 (11.02.2026) or higher

Part 2: Integration into Raindancer (only by a service partner)

This part will be carried out by your Raindancer service partner.

1. Provide your service partner with the previously noted IMEI number.
2. The service partner will register the IMEI in the Raindancer system under:
   - Menu item: **"Edit Irrigator" → "Irrigator Control"**
   - Select control type: **Irrimec Dosidis+ IP**

Revision #5
Created 1 April 2025 19:14:15 by Jens Götze - Extern
Updated 15 April 2026 15:28:00 by Frank Dühnelt